

# LUT8U-11301

LUT8

**LUMINESCENCE SENSORS** 



## Ordering information

Туре	part no.
LUT8U-11301	1047043

Other models and accessories → www.sick.com/LUT8

Illustration may differ



#### Detailed technical data

#### **Features**

Dimensions (W x H x D)	30.4 mm x 53 mm x 80 mm
Sensing distance	≤ 50 mm <sup>1)</sup>
Housing design	Large
Working range	20 mm 70 mm
Light source	LED, UV <sup>2)</sup>
Wave length	375 nm
Light emission	Long side
Light spot size	5 mm x 15 mm
Light spot direction	Vertical
Receiving filters	≤ 420 nm <sup>3)</sup>
Receiving range	450 nm 750 nm
Adjustment	Manual (rotary switch)
Output function	Light switching

 $<sup>^{1)}</sup>$  From leading edge of lens.

#### Mechanics/electronics

Supply voltage	12 V DC 30 V DC <sup>1)</sup>

 $<sup>^{1)}</sup>$  Limit values when operated in short-circuit protected network: max. 8 A.

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at T<sub>U</sub> = +25 °C.

 $<sup>^{\</sup>rm 3)}$  Filter blocks shorter wavelengths to suppress background luminescence.

 $<sup>^{\</sup>rm 2)}$  May not fall below or exceed UV tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> With light/dark ratio 1:1.

 $<sup>^{5)}\,\</sup>mathrm{Signal}$  transit time with resistive load.

<sup>&</sup>lt;sup>6)</sup> Reference voltage DC 50 V.

Ripple	< 5 V <sub>pp</sub> <sup>2)</sup>
Current consumption	< 100 mA <sup>3)</sup>
Switching frequency	2.5 kHz <sup>4)</sup>
Response time	200 μs <sup>5)</sup>
Switching output	PNP, NPN
Switching output (voltage)	PNP: HIGH = $V_{S^-} \le 3 \text{ V} / \text{LOW} = \text{approx. 0 V}$ NPN: HIGH = approx. $U_V / \text{LOW} \le 2 \text{ V}$
Switching mode	Light switching
Analog output	0 mA 13 mA
Output current I <sub>max.</sub>	100 mA
Connection type	Male connector M12, 5-pin
Protection class	II <sup>6)</sup>
Circuit protection	U <sub>V</sub> connections, reverse polarity protected Output Q short-circuit protected Interference pulse suppression
Enclosure rating	IP67
Weight	400 g
Housing material	Zinc diecast

 $<sup>^{1)}\,\</sup>mathrm{Limit}$  values when operated in short-circuit protected network: max. 8 A.

#### Ambient data

Ambient operating temperature	-10 °C +55 °C
Ambient temperature, storage	-25 °C +75 °C
Shock load	According to IEC 60068

#### Certificates

EU declaration of conformity	✓
UK declaration of conformity	✓
ACMA declaration of conformity	✓
Moroccan declaration of conformity	✓
China RoHS	✓
Photobiological safety (IEC EN 62471)	✓

## Classifications

ECLASS 5.0	27270908
ECLASS 5.1.4	27270908
ECLASS 6.0	27270908
ECLASS 6.2	27270908
ECLASS 7.0	27270908
ECLASS 8.0	27270908

<sup>&</sup>lt;sup>2)</sup> May not fall below or exceed U<sub>V</sub> tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> With light/dark ratio 1:1.


<sup>5)</sup> Signal transit time with resistive load.


<sup>&</sup>lt;sup>6)</sup> Reference voltage DC 50 V.

## **LUMINESCENCE SENSORS**


ECLASS 8.1	27270908
ECLASS 9.0	27270908
ECLASS 10.0	27270908
ECLASS 11.0	27270908
ECLASS 12.0	27270908
ETIM 5.0	EC001822
ETIM 6.0	EC001822
ETIM 7.0	EC001822
ETIM 8.0	EC001822
UNSPSC 16.0901	39121528

## Dimensional drawing










Dimensions in mm (inch)


- ① M5 threaded mounting hole, 5.5 mm deep
- ② Light spot direction
- ③ Center of optical axis
- ④ Connector M12 (rotatable up to 90°)
- ⑤ see dimensional drawings of lenses

#### Adjustments




- ① Rotary selection switch
- ② Function signal indicator (yellow), switching output
- 3 bar graph (green), power-on left-hand LED

#### Connection diagram Cd-312




#### Concept of operation Rotary switch

## 1. Position mark




Turn "Sensitivity" rotary switch clockwise until yellow LED illuminates.

#### 2. Position background



If yellow LED illuminates, turn "Sensitivity" rotary switch counter-clockwise until the yellow LED just goes out.


#### **Sensitivity setting**



#### Note

The bar graph display shows the luminescence intensity (regardless of switching threshold setting). Adjustments are intendend for luminescence background suppression.

## Sensing distance



- ① Sensing distance 10 mm
- ② Sensing distance 20 mm
- 3 Sensing distance 50 mm
- 4 Sensing distance 90 mm

## Light spot size

#### Sensing distance 50 mm Sensing distance 90 mm Sensing distance 10 mm Sensing distance 20 mm $\begin{array}{c} 2 \times 6 \\ 5 \times 10 \\ (0.2 \times 0.4) \\ \end{array} \quad \begin{array}{c} 2 \times 6 \\ 4 \times 8 \\ (0.2 \times 0.3) \end{array}$ $\begin{array}{c} 5 \times 15 \\ (0.2 \times 0.6) \\ 6 \times 16 \\ (0.2 \times 0.6) \\ | \quad (0.3 \times 0.8) \end{array}$ $\begin{array}{c} 12 \times 12 \\ (0.5 \times 0.5) \\ 6 \times 15 \\ (0.2 \times 0.6) \\ \end{array} \begin{array}{c} 13 \times 16 \\ (0.5 \times 0.6) \end{array}$ $\begin{array}{c} 3\,x\,9\\ 0.1\,x\,0.4)\\ 8\,x\,10\\ (0.1\,x\,0.4) & 8\,x\,14\\ (0.3\,x\,0.6) \end{array}$ Sensor Sensor Sensor Sensor 30 (1.2) 60 (2.4) 90 (3.5) 15 (0.6) 20 (0.8) 50 (2.0) 70 (2.8) 110 (4.3) 10 (0.4) 10 (0.4) 40 (1.6) 5 (0.2) Distance Distance Distance Distance

#### Recommended accessories

Other models and accessories → www.sick.com/LUT8

	Brief description	Туре	part no.
reflectors and optics			
	Description: Lens, 10 mm sensing distance	OBJ-LUT3-10	2016348
	Description: Lens, 20 mm sensing distance	OBJ-LUT3-20	2016349
	Description: Lens, 50 mm sensing distance	OBJ-LUT3-50	2016350
	Description: Lens, 90 mm scanning distance	0BJ-026	1001326
	• <b>Description:</b> Adapter ring for lens with M20 x 0.75 (OBJ-026/90 mm lens)	AD-OBJ-01	2017097
Mounting syst	ems		
	<ul> <li>Description: Plate G for universal clamp bracket</li> <li>Material: Steel</li> <li>Details: Steel, zinc coated</li> <li>Items supplied: Universal clamp (2022726), mounting hardware</li> <li>Usable for: W34, LUT3, KT5-2, KT10, CS8, W24-2, KT8, KT8</li> </ul>	BEF-KHS-G01	2022464
	<ul> <li>Description: Plate K for universal clamp bracket</li> <li>Material: Steel</li> <li>Details: Steel, zinc coated</li> <li>Items supplied: Universal clamp (2022726), mounting hardware</li> <li>Usable for: W11-2, W12-3, W14-2, W18-3, W23-2, W24-2, W27-3, W30, W32, W34, W36, PL50A, PL80A, P250, UC12, LUT3, KT2, KT5-2, KT8, CS8, DT2, DS30, DS40, W12-2 Laser, W16, W26, KT5</li> </ul>	BEF-KHS-K01	2022718

	Brief description	Туре	part no.		
connectors ar	connectors and cables				
	Connection type head A: Female connector, M12, 5-pin, straight, A-coded     Description: Unshielded     Connection systems: Screw-type terminals     Permitted cross-section: ≤ 0.75 mm²	DOS-1205-G	6009719		
	Connection type head A: Female connector, M12, 5-pin, angled, A-coded Description: Unshielded Connection systems: Screw-type terminals Permitted cross-section: ≤ 0.75 mm²	DOS-1205-W	6009720		
3	<ul> <li>Connection type head A: Female connector, M12, 5-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YG2A15-020VB5XLEAX	2096215		
	<ul> <li>Connection type head A: Female connector, M12, 5-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YG2A15-050VB5XLEAX	2096216		
-	Connection type head A: Female connector, M12, 5-pin, angled, A-coded Connection type head B: Flying leads Signal type: Sensor/actuator cable Cable: 10 m, 5-wire, PVC Description: Sensor/actuator cable, unshielded Application: Zones with chemicals, Uncontaminated zones	YG2A15-100VB5XLEAX	2096217		
	<ul> <li>Connection type head A: Female connector, M12, 5-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A15-020VB5XLEAX	2096239		
	<ul> <li>Connection type head A: Female connector, M12, 5-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A15-050VB5XLEAX	2096240		
	<ul> <li>Connection type head A: Female connector, M12, 5-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 10 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A15-100VB5XLEAX	2096241		
3	<ul> <li>Connection type head A: Female connector, M12, 5-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 0.6 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YG2A15- C60VB5XLEAX	2145573		
3	Connection type head A: Female connector, M12, 5-pin, angled, A-coded Connection type head B: Flying leads Signal type: Sensor/actuator cable Cable: 1 m, 5-wire, PVC Description: Sensor/actuator cable, unshielded Application: Zones with chemicals, Uncontaminated zones	YG2A15-010VB5XLEAX	2145574		
-	Connection type head A: Female connector, M12, 5-pin, angled, A-coded Connection type head B: Flying leads Signal type: Sensor/actuator cable Cable: 3 m, 5-wire, PVC Description: Sensor/actuator cable, unshielded	YG2A15-030VB5XLEAX	2145575		

# LUT8U-11301 | LUT8 LUMINESCENCE SENSORS

Brief description	Туре	part no.
Application: Zones with chemicals, Uncontaminated zones		
<ul> <li>Connection type head A: Female connector, M12, 5-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 0.6 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A15- C60VB5XLEAX	2145570
<ul> <li>Connection type head A: Female connector, M12, 5-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 3 m, 5-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A15-030VB5XLEAX	2145572

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

