

# IHM06-06NPSVT0S

IMM

**INDUCTIVE PROXIMITY SENSORS** 



## INDUCTIVE PROXIMITY SENSORS



## Ordering information

Туре	part no.
IHM06-06NPSVT0S	1114155

Other models and accessories → www.sick.com/IMM

Illustration may differ





#### Detailed technical data

#### **Features**

Housing	Cylindrical
Housing	Standard design
Diameter	Ø 6.5 mm
Sensing range S <sub>n</sub>	6 mm
Safe sensing range S <sub>a</sub>	4.86 mm
Installation type	Non-flush
Switching frequency	1,000 Hz
Connection type	Connector M8, 3-pin
Switching output	PNP
Switching output detail	PNP
Output function	NO
Electrical wiring	DC 3-wire
Enclosure rating	IP67 <sup>1)</sup>
Special features	Visual adjustment indicator, IO-Link, triple sensing range

<sup>&</sup>lt;sup>1)</sup> According to EN 60529.

## Mechanics/electronics

Supply voltage	10 V DC 30 V DC
Ripple	≤ 20 % <sup>1)</sup>
Voltage drop	$\leq$ 2 V <sup>2)</sup>
Time delay before availability	≤ 80 ms

 $<sup>^{1)}</sup>$  Of  $V_{S}$ .

<sup>&</sup>lt;sup>2)</sup> With Ia = 200 mA.

 $<sup>^{\</sup>rm 3)}$  Supply voltage  $\rm U_B$  and constant ambient temperature Ta.

Hysteresis	1 % 10 %
Reproducibility	≤ 2 % <sup>3)</sup>
Temperature drift (of S <sub>r</sub> )	≤ 10 %
EMC	EN 60947-5-2
Continuous current I <sub>a</sub>	≤ 200 mA
Short-circuit protection	✓
Power-up pulse protection	✓
Shock and vibration resistance	30 g, 11 ms / 10 55 Hz, 1 mm
Ambient operating temperature	-25 °C +70 °C
Housing material	Stainless steel V2A, DIN 1.4305 / AISI 303
Sensing face material	Plastic, LCP
Housing length	50 mm
UL File No.	NRKH.E348498

 $<sup>^{1)}</sup>$  Of  $V_{S}$ .

## Safety-related parameters

MTTF <sub>D</sub>	1,330 years
DC <sub>avg</sub>	0 %

## Communication interface

Communication interface	IO-Link V1.1
Communication Interface detail	COM2 (38,4 kBaud)
Cycle time	10.4 ms
Process data length	1 Byte
Process data structure	Bit 0 = Sr reached Bit 1 = Sa reached

## Reduction factors

Note	The values are reference values which may vary
St37 steel (Fe)	1
Stainless steel (V2A, 304)	Approx. 0.75
Aluminum (AI)	Approx. 0.5
Copper (Cu)	Approx. 0.43
Brass (Br)	Approx. 0.54

#### Installation note

Remark	Associated graphic see "Installation"
Α	12 mm
В	35 mm
c	6.5 mm
D	18 mm
E	12 mm

<sup>&</sup>lt;sup>2)</sup> With Ia = 200 mA.

 $<sup>^{\</sup>rm 3)}$  Supply voltage  ${\rm U_B}$  and constant ambient temperature Ta.

# IHM06-06NPSVTOS | IMM


INDUCTIVE PROXIMITY SENSORS

F	48 mm
Certificates	
EU declaration of conformity	✓
UK declaration of conformity	✓
ACMA declaration of conformity	✓
Moroccan declaration of conformity	✓
China RoHS	✓
IO-Link certificate	✓

#### Classifications

ECLASS 5.0	27270101
ECLASS 5.1.4	27270101
ECLASS 6.0	27270101
ECLASS 6.2	27270101
ECLASS 7.0	27270101
ECLASS 8.0	27270101
ECLASS 8.1	27270101
ECLASS 9.0	27270101
ECLASS 10.0	27270101
ECLASS 11.0	27270101
ECLASS 12.0	27274001
ETIM 5.0	EC002714
ETIM 6.0	EC002714
ETIM 7.0	EC002714
ETIM 8.0	EC002714
UNSPSC 16.0901	39122230

## Installation note Fixing with setscrew




- ① Sensing face
- 2 Recommended setscrew: M3, flat point
- ③ Display LED

Sensor type	Mounting area (L)	Max. tightening torque (M <sub>max</sub> )
IHM06-04N****K	8 mm 21 mm	≤ 0.4 Nm
IHM06-04N***T0K	8 mm 32 mm	≤ 0.4 Nm


Sensor type	Mounting area (L)	Max. tightening torque ( $M_{max}$ )
IHM06-04N****S	8 mm 32 mm	≤ 0.4 Nm
IHM06-04N***TOS	8 mm 42 mm	≤ 0.4 Nm
IHM06-06N****K	12 mm 21 mm	≤ 0.4 Nm
IHM06-06N***TOK	12 mm 32 mm	≤ 0.4 Nm
IHM06-06N****S	12 mm 32 mm	≤ 0.4 Nm
IHM06-06N***TOS	12 mm 42 mm	≤ 0.4 Nm


## Installation note Mounting using BEF-KH-M06 bracket



Sensor type	Mounting adapter	Overrun (P)	Max. tightening torque (M <sub>max</sub> )
IHM06-04N***** IHM06-06N*****	BEF-KH-M06, part no. 2101067	≥ 4 mm	≤ 0.6 Nm

## Installation note Non-flush installation






## Connection diagram Cd-002




## Response diagram




Distance of target edge to center of active face in mm (inch)

All dimensions in mm (inch)

## Functional principle Installation aid



## Dimensional drawing IHM06, standard variant, non-flush, male connector





Dimensions in mm (inch)

- ① Connection
- 2 function indicator

#### Recommended accessories

Other models and accessories → www.sick.com/IMM

	Brief description	Туре	part no.
Mounting systems			
	<ul> <li>Material: Plastic</li> <li>Details: Plastic (PA6)</li> <li>Items supplied: Without mounting hardware</li> <li>Usable for: Round sensors with 6.5 mm housing diameter without fixed stop</li> </ul>	BEF-KH-M06	2101067

	Brief description	Туре	part no.	
connectors and cables				
	<ul> <li>Number of slots: 4</li> <li>Slot connection type: M8, 3-pin, A-coded, female connector</li> <li>Items supplied: 5 x labeling plates</li> <li>Description: Unshielded</li> </ul>	Y8A34A2- C2A8000XXX	2115733	
Control of the second	<ul> <li>Number of slots: 4</li> <li>Slot connection type: M8, 3-pin, A-coded, female connector</li> <li>Items supplied: 5 x labeling plates</li> <li>Cable: 5 m, 6-wire, PUR, halogen-free</li> <li>Description: Unshielded</li> <li>Application: Drag chain operation</li> </ul>	Y8A34A2- LXXXUAA050	2115727	
	<ul> <li>Number of slots: 6</li> <li>Slot connection type: M8, 3-pin, A-coded, female connector</li> <li>Items supplied: 5 x labeling plates</li> <li>Description: Unshielded</li> </ul>	Y8A36A2- C2A8000XXX	2115734	
CHE	<ul> <li>Number of slots: 6</li> <li>Slot connection type: M8, 3-pin, A-coded, female connector</li> <li>Items supplied: 5 x labeling plates</li> <li>Cable: 5 m, 8-wire, PUR, halogen-free</li> <li>Description: Unshielded</li> <li>Application: Drag chain operation</li> </ul>	Y8A36A2- LXXXUBA050	2115728	
We.	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YF8U13-020UA1XLEAX	2094782	
No.	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YF8U13-050UA1XLEAX	2094788	
0	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13-020VA1XLEAX	2095860	
No.	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13-050VA1XLEAX	2095884	
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-020UA1XLEAX	2094794	
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-050UA1XLEAX	2095586	
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> </ul>	YG8U13-020VA1XLEAX	2096165	

	Brief description	Туре	part no.
	Application: Zones with chemicals, Uncontaminated zones		
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YG8U13-050VA1XLEAX	2096166
100	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YF8U13-020UA1M2A13	2096169
100	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YF8U13-050UA1M2A13	2096170
10 PG	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13-020VA1M2A13	2096605
10 PG	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13-050VA1M2A13	2096606
36	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-020UA1M2A13	2095748
No No	Connection type head A: Female connector, M8, 3-pin, straight, A-coded Connection type head B: Male connector, M8, 3-pin, straight, A-coded Signal type: Sensor/actuator cable Cable: 2 m, 3-wire, PUR, halogen-free Description: Sensor/actuator cable, unshielded Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation	YF8U13-020UA1M8U13	2096304
R. R.	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M8, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YF8U13-050UA1M8U13	2096308
96	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Male connector, M8, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 2 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-020UA1M8U13	2107781
100	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-050UA1M2A13	2122842
1. 10	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 3 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> </ul>	YF8U13-030UA1M2A13	2144589

# IHM06-06NPSVT0S | IMM

## INDUCTIVE PROXIMITY SENSORS

	Brief description	Туре	part no.
	Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation		
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 0.6 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13- C6OUA1XLEAX	2145889
3	<ul> <li>Connection type head A: Female connector, M8, 3-pin, angled, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 3 m, 3-wire, PUR, halogen-free</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Uncontaminated zones, Zones with oils and lubricants, Robot, Drag chain operation</li> </ul>	YG8U13-030UA1XLEAX	2145891
0	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 0.6 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13- C60VA1XLEAX	2146368
10 to	<ul> <li>Connection type head A: Female connector, M8, 3-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 3-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 1 m, 3-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF8U13-010VA1M2A13	2146381

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

